

PROTOCOL of CONVERTIBLE CAMERA and PAN/TILT SYSTEM
Ver2.45 (Oct/22,2015)

AW-HE130/AW-HE60/AW-HE120/AW-HE50
AW-HE40/AW-HE65/AW-HE70/AW-UE70

Panasonic Corporation

Specifications are subject to change without notice.

Camera Control Protocol

This is a program to control Panasonic Convertible Camera system from PC by serial communication.

Method	Half Duplex
Communication Speed	9600bps
Data bit	8bit
Stop bit	1bit
Prity	None
Flow contorol	None

(Electrical Specification)

Compatible with RS422

2line system(TXD/send, RXD/Recieve)

(Process)

- (1) PC — Command → CAMERA
- (2) CAMERA — ACK(H'06) → PC
- (3) CAMERA Processes "Command"
- (4) CAMERA — Command' → PC

Normally it is processed as mentioned above, but in case of error, it ends by replying error code(*1) in (4).

Command and Command' are not always the same.

Camera does not accept a command unless command process finishes and returns the return code

(*1)Error code

Item	Error code	Contents
Unsupported	[STX]ER1[ETX]	The Command is not supported by CAMERA.
System busy	[STX]ER2[ETX]	CAMERA can not process the command for running the other processing.
Out of range	[STX]ER3[ETX]	Data is out of range.

(5)Pattern 5 (Other Menus)

In order of Command, ":", Number Command(2 Bytes), ":", Data. Data length=2 Bytes.

```
[STX]  O   S   D   :   ?   ?   :   ?   ?   [ETX]
H'02  H'4F H'53 H'44 H'3A H'** H'** H'3A H'** H'** H'03
```

In this pattern, numbers at rear part of command (6th and 7th letters) are the command and Data follows by 2bytes (9th and 10th letters)

(6)Pattern 6 (Questions to Camera)

There is only Command, not Data

```
[STX]  Q   ?   ?   [ETX]
H'02  H'51 H'** H'** H'03
```

This Command requires the programmed number of the Camera and Camera returns adding Data.

Data is 2 Bytes but there are same exceptions. It is specified as Q(H'51) -> O(H'4F).

(7)Pattern 7 (Questions to Camera 2)

In order of Command, ":", number of Command. No Data. Command from Camera is with Data.

```
[STX]  Q   S   D   :   ?   ?   [ETX]
H'02  H'51 H'53 H'44 H'3A H'** H'** H'03
```

This Command also requires the programmed number of the Camera and the Command is converted into numbers. It can be programmed only by Camera User Mode and is Data length , which Camera returns is 2 Bytes.(There are same exceptions.) It is Q(H'51) -> O(H'4F) same as (7) . When Camera receives unprocessable number Command, it returns as Data = number Command.

a) PC -> CAMERA

```
[STX]  Q   S   D   :   1   4   [ETX]
H'02  H'51 H'53 H'44 H'3A H'31 H'34 H'03
```

b) CAMERA -> PC

```
[STX]  O   S   D   :   1   4   :   1   4   [ETX]
H'02  H'4F H'53 H'44 H'3A H'31 H'34 H'3A H'31 H'34 H'03
```

(8)Pattern 8 (Related to Contact Closer P/T)

There is only Command, not Data

```
[STX]  H   ?   ?   [ETX]
H'02  H'48 H'** H'** H'03
```

Command for Lens I/F Card (AW-PB308) and control of lens for AW-E655. Camera repeats the same Command.

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
MODEL NUMBER	---		QID	OID:[Data]			Returns model No. by ASCII	Ex. OID:AW-HE50	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
SOFTWARE VERSION	---		QSV	OSV:[Data]			Software Version		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
AWC/AWB SET	OWS	OWS ER3:OWS		---	---	AWC/AWB Start AWC/AWB OK AWC/AWB NG	---	Response Command returns when AWC/AWB finish	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
ABC/ABB SET	OAS	OAS ER3:OAS		---	---	ABC/ABB Start ABC/ABB OK ABC/ABB NG	---	Response Command returns when ABC/ABB finish	---	---	V1.00	V1.00	V1.00	V1.00
AWC MODE			QAW	OAW:[Data]	0 1 2 3 4 5 6 7 8 9	ATW AWC A AWC B ATW PRESET 3200K PRESET 5600K PRESET 4500K PRESET 6000K PRESET 2800K VAR	ATW --- AWC A AWC B PRESET 3200K PRESET 5600K PRESET 4500K PRESET 6000K PRESET 2800K VAR	Be careful because Data of control and question is different.	V1.00 supports only ATW, AWC A, AWC B	V3.00 supports only ATW, AWC A, AWC B	V1.00 supports only ATW AWC A AWC B PRESET 3200K PRESET 5600K	V1.00 supports only ATW AWC A AWC B PRESET 3200K PRESET 5600K VAR	V1.00 supports only ATW AWC A AWC B PRESET 3200K PRESET 5600K VAR	V1.00 supports only ATW AWC A AWC B PRESET 3200K PRESET 5600K VAR
DETAIL			QDT	ODT:[Data]	0 1 2	OFF LOW HIGH HC1500, HC1800, HE130	OFF LOW HIGH		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
HD DETAIL			QHD	OHD:[Data]	0 1 2	AW-HE870 OFF LOW HIGH			---	---	---	---	---	---

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks					
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70
GAIN UP	OGU: [Data]	QGU	OGU: [Data]		00h AGC Low 01h AGC High 08h 0dB - 11h 9dB - 1Ah 18dB - 26h 30dB 27h N/Eye Low N/Eye 28h N/Eye High 80h AGC ON <u>AW-HE130, HE40, HE70</u> 08h 0dB - 11h 9dB - 1Ah 18dB - 38h 48dB 80h AGC ON <u>AW-HE870</u> 02h -6dB - 1Ah 18dB 80h AGC ON		V1.00 supports only 08 (0dB) -1A (18dB), 80 (AGC ON)	V3.00 supports only 08 (0dB) -1A (18dB), 80 (AGC ON)	V1.00 supports only 08 (0dB) -1A (18dB), 80 (AGC ON)	V1.00 supports only 08 (0dB) -2C (36dB), 80 (AGC ON)	V1.00 supports only 08h:0dB-38h:48dB 80h:AGC ON Use only 3dB Step.	V1.00 supports only 08h:0dB-38h:48dB 80h:AGC ON Use only 3dB Step.	
SHUTTER	OSH: [Data]	QSH	OSH: [Data]		0h OFF 1h 1/50 2h 1/60 3h 1/100 (NTSC) , 1/120 (PAL) 4h 1/120 (NTSC) , 1/100 (PAL) 5h 1/250 6h 1/500 7h 1/1000 8h 1/2000 9h 1/4000 Ah 1/10000 Bh Synchro-Scan Ch ELC (AUTO ND) Dh 1/24 Eh 1/25 Fh 1/30		V1.00 supports only 0 (OFF), 3 (1/100 NTSC) (1/120 PAL), 5 (1/250)	V3.00 supports only 0 (OFF), 3 (1/100 NTSC) (1/120 PAL), 5 (1/250) B (Synchro-Scan)	V1.00 supports only 0 (OFF), 3 (1/100 NTSC) (1/120 PAL), 5 (1/250) C (ELC)	V1.00 (59.94p/59.94i) 0 (OFF) 3 (1/100) 4 (1/120) 5 (1/250) C (ELC) (29.97p) 0 (OFF) 2 (1/60) 4 (1/120) 5 (1/250) D (1/24) (50p/50i) 0 (OFF) 2 (1/60) 3 (1/120) 5 (1/250) C (ELC) (25p) 0 (OFF) 2 (1/60) 3 (1/120) 5 (1/250) C (ELC) E (1/25)	V1.00 supports only 0 (OFF), 3 (1/100 NTSC) (1/120 PAL), 5 (1/250) B (Synchro-Scan)	V1.00 supports only 0 (OFF), 3 (1/100 NTSC) (1/120 PAL), 5 (1/250) B (Synchro-Scan)	

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
SYNCHRO SCAN	OMS: [Data]		OMS	OMS: [Data]	001h - 105h 001h - 137h 721h - 8DFh 721h - 8DFh 721h - 8DFh 001h - 1ABh 001h - 1C2h	<u>N Model (59Hz)</u> 60. 34Hz - 15. 75kHz <u>E. MC Model (50Hz)</u> 50. 24Hz - 15. 63kHz <u>AK-HC1500/HC1800 (60Hz)</u> 60. 32Hz/60. 32Hz - 150. 0Hz/149. 2Hz <u>AK-HC1500/HC1800 (50Hz)</u> 50. 27Hz/50. 27Hz - 125. 0Hz/124. 3Hz <u>AK-HC1500. HC1800 (FILM MENU)</u> 358. 1deg - 144. 0deg <u>HE-100N</u> 60Hz - 248. 8Hz <u>HE-100E. MC</u> 50. 0Hz - 250. 0Hz		V1. 00 (N Model) 001h (60. 17Hz) - OFFh (644. 25Hz)	V3. 00 (59Hz) 001h (60. 17Hz) - OFFh (644. 25Hz)	V1. 00 (59Hz) 001h (60. 17Hz) - OFFh (646. 21Hz)	V1. 00 (59Hz) 001h (60. 15Hz) - OFFh (642. 21Hz)	V1. 00 (59. 94Hz) 001h (59. 94Hz) - OFFh (660. 09Hz)	V1. 00 (59. 94Hz) 001h (59. 94Hz) - OFFh (660. 09Hz)	V1. 00 (59. 94Hz) 001h (59. 94Hz) - OFFh (660. 09Hz)
FIELD/FRAME					0	Field	Only User Mode	---	---	---	---	---	---	
V. RESOLUTION	OFR: [Data]		OFF	OFF: [Data]	1	Frame1		---	---	---	---	---	---	
					2	Frame2		---	---	---	---	---	---	
					0	Normal	Only Halogen, Fluorescent, Outdoor mode	---	---	---	---	---	---	
					1	(Fine)		---	---	---	---	---	---	
					2	Fine		---	---	---	---	---	---	
IRIS AUTO/MANUAL	ORS: [Data]		QRS	ORS: [Data]	0	Manual	V1. 00	V3. 00	V1. 00	V1. 00	V1. 00	V1. 00	V1. 00	
					1	Auto								
MANUAL IRIS VOLUME	ORV: [Data]		QRV	ORV: [Data]	000h	close	V1. 00	V3. 00	V1. 00	V1. 00	V1. 00	V1. 00	V1. 00	
					3FFh	open								
PICTURE LEVEL A. IRIS LEVEL	OSD: 48: [Data]		QSD: 48	OSD: 48: [Data]	00h	-50	V1. 00 Data/10	V3. 00 Data/10	V1. 00 Data/5	V1. 00	V1. 00 Data/5	V1. 00 Data/5	V1. 00 Data/5	
					-	-								
					31h	-1								
					32h	0								
					33h	+1								
					-	-								
					64h	+50								
					00h	<u>AK-HC1500. HC1800</u> 0								
					-	-								
					64h	100								

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks							
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70		
LIGHT PEAK/AVG A. IRIS PEAK/AVG	OPV: [Data]		QPA	OPA: [Data]	00h - 31h 32h 33h - 64h 00h - 64h	P50 - P1 0 A1 - A50 <u>AK-HC1500, HC1800</u> 0 - 100									
LIGHT AREA A. IRIS AREA	ORA: [Data]		QAR	OAR: [Data]	0 1 5 6 7	ALL Center Top Cut Bottom Cut R/L Cut									
MEGA/POS1	ONP: [Data]		QNP	ONP: [Data]	0 1	Positive Negative									
R PEDESTAL	ORD: [Data]		QRD	ORD: [Data]	00h - 1Eh - 3Ch	-30 - 0 - +30				V1.00 Data*5	V1.00 Data*5 supports only 0A(-100) - 32(+100)				
B PEDESTAL	OBD: [Data]		QBD	OBD: [Data]	00h - 1Eh - 3Ch	-30 - 0 - +30				V1.00 Data*5	V1.00 Data*5 supports only 0A(-100) - 32(+100)				
R GAIN	ORG: [Data]		QGR	OGR: [Data]	00h - 1Eh - 3Ch	-30 - 0 - +30		V2.00	V3.00	V1.00 Data*5	V1.00 Data*5	V1.00	V1.00		
B GAIN	OGB: [Data]		QGB	OGB: [Data]	00h - 1Eh - 3Ch	-30 - 0 - +30		V 2.00	V3.00	V1.00 Data*5	V1.00 Data*5	V1.00	V1.00		
T PEDESTAL	OTD: [Data]		QTD	OTD: [Data]	00h - 1Eh - 3Ch	-30 - 0 - +30		V1.00 Data/3	V3.00 Data/3	V1.00 Data*5	V1.00 Data*5	V1.00 Data/3	V1.00 Data/3		
H PHASE	OHP: [Data]		QHP	OHP: [Data]	000h - 3FFh	-206 - +49		V1.00	V3.00	V1.00	V1.00				V1.00
SC COARSE	OSC: [Data]		QSC	OSC: [Data]	0 1 2 3 4 <u>AW-HE870</u> 5 6 7 8	2(90deg) 3(180deg) 4(270deg) 1(0deg) - <u>AW-HE870</u> 45deg (HE870) 135deg (HE870) 225deg (HE870) 315deg (HE870)	1(0deg) 2(90deg) 3(180deg) 4(270deg)	Be careful because Data of control and question is different.	V1.00	V3.00					

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
SC FINE	OSN: [Data]		QSN	OSN: [Data]	000h 001h 002h - 200h - 3FFh <u>AW-HE870</u> 000h - 007h 008h - 200h - 3FBh 3FCh - 3FFh	-511 -511 -511 0 - +511 <u>AW-HE870</u> -127 - -127 -126 - 0 - +126 +127 - +127	(AW-HE870) One value of "Data Contents" is added by four "Data" counts.	V1.00	V3.00					
CHROMA LEVEL	OCG: [Data]		QCG	OCG: [Data]	00 - 03 - 06	-3 - 0 - +3		V1.00	V3.00	V1.00			V1.00	V1.00
SCENE FILE	XSF: [Data]		QSF	OSF: [Data]	0 1 2 3 4 5 6 7 0 1 2 3 4	Halogen Fluorescent Outdoor User <u>HC1500, HC1800</u> PRESET USER1 USER2 CURRENT	Halogen Fluorescent Outdoor User Halogen Fluorescent Outdoor User <u>HC1500, HC1800</u> PRESET USER1 USER2 CURRENT	Be careful because Data of control and question is different.	V1.00 supports only Halogen=MANUAL1, Fluorescent=MANUAL2, Outdoor=MANUAL3, User=FULLAUTO,	V3.00 supports only Halogen=MANUAL1, Fluorescent=MANUAL2, Outdoor=MANUAL3, User=FULLAUTO,	V1.00 supports only Halogen=Scene1, Fluorescent=Scene2, Outdoor=Scene3, User=Scene4,	V1.00 supports only Halogen=Scene1, Fluorescent=Scene2, Outdoor=Scene3, User=Scene4,	V1.00 supports only Halogen=MANUAL1, Fluorescent=MANUAL2, Outdoor=MANUAL3, User=FULLAUTO,	V1.00 supports only Halogen=MANUAL1, Fluorescent=MANUAL2, Outdoor=MANUAL3, User=FULLAUTO,
GAMMA	OSD:00: [Data]		QSD:00	OSD:00: [Data]	00h - 0Ah - 14h	0.35 - 0.45 - 0.55								
KNEE POINT	OSD:08: [Data]		QSD:08	OSD:08: [Data]	FFh 00h - 0Ah 0Bh	Dynamic 88% - 98%	Dynamic 88% - 98% ----	Be careful because Data of control and question is different.						
WHITE CLIP	OSD:09: [Data]		QSD:09	OSD:09: [Data]	00h - 0Fh	95% - 110%								
H. DTL LEVEL H	OSD:0A: [Data]		QSD:0A	OSD:0A: [Data]	01h - 3Fh	1 - 63					V1.00 Support Only 02(0)-3F(63)			
HD H. DTL LEVEL H	OSD:0B: [Data]		QSD:0B	OSD:0B: [Data]	01h - 3Fh	1 - 63								
V DTL LEVEL H	OSD:0E: [Data]		QSD:0E	OSD:0E: [Data]	01h - 1Fh	1 - 31					V1.00 Support Only 02(0)-1F(32)			
HD V DTL LEVEL H	OSD:0F: [Data]		QSD:0F	OSD:0F: [Data]	01h - 1Fh	1 - 31								

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
H. DTL LEVEL L	OSD:12:[Data]		QSD:12	OSD:12:[Data]	00h - 3Eh	0 - 62				V1.00 Support Only 01(0)-3E(62)				
HD H. DTL LEVEL L	OSD:13:[Data]		QSD:13	OSD:13:[Data]	00h - 3Eh	0 - 62								
V DTL LEVEL L	OSD:16:[Data]		QSD:16	OSD:16:[Data]	00h - 1Eh	0 - 30				V1.00 Support Only 01(0)-1E(30)				
HD V DTL LEVEL L	OSD:17:[Data]		QSD:17	OSD:17:[Data]	00h - 1Eh	0 - 30								
DETAIL BAND	OSD:1E:[Data]		QSD:1E	OSD:1E[Data]	01 - 05	01 - 05				V1.00				
HD DETAIL BAND	OSD:1F:[Data]		QSD:1F	OSD:1F[Data]	01 - 05	01 - 05								
NOISE SUPPRESS /CRISP	OSD:22:[Data]		QSD:22	OSD:22:[Data]	00h - 3Ch 00h - 1Fh	0 - 60 <u>AK-HC1500, HC1800</u> 0 - 31				V1.00 Support Only 00(0)-07(7)	V1.00			
HD NOISE SUPPRESS /CRISP	OSD:23:[Data]		QSD:23	OSD:23:[Data]	00h - 0Ah	<u>AW-HE870</u> 0 - 10								
LEVEL DEPENDENT	OSD:26:[Data]		QSD:26	OSD:26:[Data]	00h - 19h <u>AK-HC1500, HC1800</u> 00h - 0Fh <u>AK-HC3800</u> 00 - 1E	00% - 25% <u>AK-HC1500, HC1800</u> 0% - 15% <u>AK-HC3800</u> 0% - 30%								
HD LEVEL DEPENDENT	OSD:27:[Data]		QSD:27	OSD:27:[Data]	00h - 19h	<u>AW-HE870</u> 00% - 25%								
CHROMA DETAIL	OSD:2A:[Data]		QSD:2A	OSD:2A:[Data]	00h - 0Fh	00 - 15								
HD CHROMA DETAIL	OSD:2B:[Data]		QSD:2B	OSD:2B:[Data]	00h - 0Fh	00 - 15								
HD DARK DETAIL	OSD:2D:[Data]		QSD:2D	OSD:2D:[Data]	00 - 05 <u>AK-HC3800</u> 00 - 07	0 - 5 <u>AK-HC3800</u> 0 - 7								

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks							
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70		
DARK DETAIL	OSD:2E:[Data]		QSD:2E	OSD:2E:[Data]	00 - 05		0 - 5								
MATRIX (R-G)	OSD:2F:[Data]		QSD:2F	OSD:2F:[Data]	00h - 1Fh - 3Eh		-31 - 0 +31			V1.00					
MATRIX (R-B)	OSD:30:[Data]		QSD:30	OSD:30:[Data]	00h - 1Fh - 3Eh		-31 - 0 +31			V1.00					
MATRIX (G-R)	OSD:31:[Data]		QSD:31	OSD:31:[Data]	00h - 1Fh - 3Eh		-31 - 0 +31			V1.00					
MATRIX (G-B)	OSD:32:[Data]		QSD:32	OSD:32:[Data]	00h - 1Fh - 3Eh		-31 - 0 +31			V1.00					
MATRIX (B-R)	OSD:33:[Data]		QSD:33	OSD:33:[Data]	00h - 1Fh - 3Eh		-31 - 0 +31			V1.00					
MATRIX (B-G)	OSD:34:[Data]		QSD:34	OSD:34:[Data]	00h - 1Fh - 3Eh		-31 - 0 +31			V1.00					
FLARE R	OSD:35:[Data]		QSD:35	OSD:35:[Data]	00h - 64h <u>AK-HC3500</u> 9C ~ FF 00 01 ~ 64		0 - 100 <u>AK-HC3500</u> -100 ~ -1 0 +1 ~ +100								
FLARE G	OSD:36:[Data]		QSD:36	OSD:36:[Data]	00h - 64h <u>AK-HC3500</u> 9C ~ FF 00 01 ~ 64		0 - 100 <u>AK-HC3500</u> -100 ~ -1 0 +1 ~ +100								
FLARE B	OSD:37:[Data]		QSD:37	OSD:37:[Data]	00h - 64h <u>AK-HC3500</u> 9C ~ FF 00 01 ~ 64		0 - 100 <u>AK-HC3500</u> -100 ~ -1 0 +1 ~ +100								

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
FLARE SW	OSA:11:[Data]		QSA:11	OSA:11:[Data]	0 1		OFF ON							
CLEAN DNR	OSD:3A:[Data]		QSD:3A	OSD:3A:[Data]	00 01 02		OFF LOW HIGH	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	
HD CLEAN DNR	OSD:3B:[Data]		QSD:3B	OSD:3B:[Data]	00 01 02		OFF LOW HIGH							
2D LPF	OSD:3F:[Data]		QSD:3F	OSD:3F:[Data]	00 01 02		OFF LOW HIGH							
CORNER DETAIL	OSD:43:[Data]		QSD:43	OSD:43:[Data]	00 01		OFF ON							
PRECISION DETAIL /SLIM DETAIL	OSD:44:[Data]		QSD:44	OSD:44:[Data]	00 01 02 00 01 02		OFF LOW HIGH <u>AK-HC1500_HC1800</u> OFF ON ON							
HD PRECISION DETAIL /HD SLIM DETAIL	OSD:45:[Data]		QSD:45	OSD:45:[Data]	00 01 02		<u>AW-HE870</u> OFF LOW HIGH							
BLACK STRETCH	OSD:46:[Data]		QSD:46	OSD:46:[Data]	00 01		OFF ON							
HIGH LIGHT CHROMA	OSD:49:[Data]		QSD:49	OSD:49:[Data]	00 01 02		OFF LOW HIGH							
FLESH NOISE SUPPRESS	OSD:4B:[Data]		QSD:4B	OSD:4B:[Data]	00 01 02		OFF LOW HIGH			V1.00				
FLESH DETAIL FLESH DTL LEVEL					00 01 02		LOW MID HIGH							
HD FLESH NOISE SUPPRESS	OSD:4C:[Data]		QSD:4C	OSD:4C:[Data]	00 01 02		OFF LOW HIGH							
IRIS FOLLOW	---		QSD:4F	OSD:4F:[Data]	00h - FFh	---	Close - Open	This Command can't be used through AW- RP400.	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
CONTRAST (GAMMA)	OSD:50:[Data]		QSD:50	OSD:50:[Data]	00 01 02		LOW MID HIGH	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	
FLESH TONE	OSD:52:[Data]		QSD:52	OSD:52:[Data]	00 - 03 - 06		-3 0 - +3							
DETAIL SELECT	OSD:54:[Data]		QSD:54	OSD:54:[Data]	00 01		Normal Super DTL							
NOISE SUPPRESS	OSD:55:[Data]		QSD:55	OSD:55:[Data]	00 01 02		OFF LOW HIGH							

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks					
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70
FLESH NOSE SUPPRESS	OSD:56:[Data]	QSD:56	OSD:56:[Data]	00	OFF								
DTL FLESH SUPPRESS				01	LOW								
ZEBRA INDICATER	OSD:60:[Data]	QSD:60	OSD:60:[Data]	00	OFF	with studio card							
ZEBRA1 LEVEL	OSD:61:[Data]	QSD:61	OSD:61:[Data]	01	ON								
ZEBRA2 LEVEL	OSD:62:[Data]	QSD:62	OSD:62:[Data]	02	70%	with studio card							
SAFETY ZONE	OSD:63:[Data]	QSD:63	OSD:63:[Data]	27h	109%								
				01h	71%	with studio card							
EVF OUTPUT	OSD:64:[Data]	QSD:64	OSD:64:[Data]	02	110%								
OUTPUT SELECT	OSD:65:[Data]	QSD:65	OSD:65:[Data]	03	1	with studio card							
				04	2								
CHARGE TIME	OSD:68:[Data]	QSD:68	OSD:68:[Data]	05	3								
				06	4								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	07	5								
				08	OFF								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	00	AUTO								
				01	PAL								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	02	2s								
				03	1s								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	04	1/2s								
				05	1/4s								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	06	1/8s								
				07	1/15s								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	08	1/30s								
				09	OFF								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	10	AUTO								
				11	33dB (HBK50), N/Eye (E300/A)								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	12	N/Eye L (E600, E750, E655, E860)								
				13	N/Eye H (E600, E750, E655, E860)								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	14	AW-HE40/HE65/HE70								
				15	(OFF)								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	16	6dB								
				17	12dB								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	18	18dB								
				19	24dB								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	20	30dB								
				21	36dB								
AGC MAX	OSD:69:[Data]	QSD:69	OSD:69:[Data]	22	42dB								
				23	48dB								

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks							
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70		
ASPECT RATIO	OSD:70:[Data]		QSD:70	OSD:70:[Data]	00 01		16:9 4:3								
FAN	OSD:71:[Data]		QSD:71	OSD:71:[Data]	00 01 02		OFF ON <u>AK-HC1500_HC1800</u> OFF AUTO ON								
ATW SPEED	OSD:72:[Data]		QSD:72	OSD:72:[Data]	00 01 02 03 04		Slow2 Slow1 Middle Fast1 Fast2								
COLOR BAR/CAMERA	DCB:[Data]		QBR	OBR:[Data]	0 1 2 3		Camera Color Bar Test Close(Camera)		V1.00 supports only 0(Camera), 1(Color Bar)	V3.00 supports only 0(Camera), 1(Color Bar)	V1.00 supports only 0(Camera), 1(Color Bar)	V1.00 supports only 0(Camera), 1(Color Bar)	V1.00 supports only 0(Camera), 1(Color Bar)	V1.00 supports only 0(Camera), 1(Color Bar)	
MENU	DUS:[Data]		QUS	OUS:[Data]	0 1 2		OFF ON ON ByBrowser		V1.00 supports only 0(OFF), 1(ON)	V3.00 supports only 0(OFF), 1(ON)	V1.00 supports only 0(OFF), 1(ON)	V1.00 supports only 0(OFF), 1(ON)	V1.00 supports only 0(OFF), 1(ON)	V1.00 supports only 0(OFF), 1(ON)	
BAR SETUP	DCS:[Data]		QCS	OCS:[Data]	0 1		0.0% 7.5%				V1.00	V1.00			
MENU SW	DPG:[Data]				1				"DPG" is equal to "DPG:1".	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
ITEM SW	DIT:[data]				1				"DIT" is equal to "DIT:1".	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
YES SW	DUP:[Data]				1h Ah		1Step 10Step		"DUP" is equal to "DUP:1".	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
NO SW	DDW:[Data]				1h Ah		1Step 10Step		"DDW" is equal to "DDW:1".	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
PAN (LEFT)	HPL						move to left								
PAN (RIGHT)	HPR						move to right								
PAN (STOP)	HPS						stop pan								
TILT (UP)	HTU						move to up								

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
TILT (DOWN)	HTD		---		---	move to down		---	---	---	---	---	---	---
TILT (STOP)	HTS		---		---	stop tilt		---	---	---	---	---	---	---
ZOOM (TELE)	HZT		---		---	move to tele		V1.00	V3.00	---	---	V1.00	V1.00	
ZOOM (WIDE)	HZW		---		---	move to wide		V1.00	V3.00	---	---	V1.00	V1.00	
ZOOM (STOP)	HZS		---		---	stop zoom		V1.00	V3.00	---	---	V1.00	V1.00	
ZOOM SPEED	LZS: [Data]		---		0 - 9	Slow - Fast		V1.00	V3.00	---	---	V1.00	V1.00	
FOCUS (FAR)	HFF		---		---	move to far		V1.00	V3.00	---	---	V1.00	V1.00	
FOCUS (NEAR)	HFN		---		---	move to near		V1.00	V3.00	---	---	V1.00	V1.00	
FOCUS (STOP)	HFS		---		---	stop focus		V1.00	V3.00	---	---	V1.00	V1.00	
FOCUS SPEED	LFS: [Data]		---		0 - 9	Slow - Fast		V1.00	V3.00	---	---	V1.00	V1.00	
SAVE LENS PSITION to PRESET	LPS: [Data]		---		01 02 03 04 05	Save to Preset1 Save to Preset2 Save to Preset3 Save to Preset4 Save to Preset5		---	---	---	---	---	---	

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks					
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70
Recall LENS PRESET	LPM: [Data]				00 01 02 03 04 05	Recall Current Recall Preset1 Recall Preset2 Recall Preset3 Recall Preset4 Recall Preset5							
COLOR MATRIX R GAIN /COLOR CORRECTION R SATURATION	OSD:86: [Data]		QSD:86	OSD:86: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX R PHASE /COLOR CORRECTION R PHASE	OSD:87: [Data]		QSD:87	OSD:87: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX R_YI GAIN /COLOR CORRECTION R_YI SATURATION	OSD:88: [Data]		QSD:88	OSD:88: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX R_YI PHASE /COLOR CORRECTION R_YI PHASE	OSD:89: [Data]		QSD:89	OSD:89: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX YI GAIN /COLOR CORRECTION YI SATURATION	OSD:8A: [Data]		QSD:8A	OSD:8A: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX YI PHASE /COLOR CORRECTION YI PHASE	OSD:8B: [Data]		QSD:8B	OSD:8B: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX YI_G GAIN /COLOR CORRECTION YI_G SATURATION	OSD:8C: [Data]		QSD:8C	OSD:8C: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX YI_G PHASE /COLOR CORRECTION YI_G PHASE	OSD:8D: [Data]		QSD:8D	OSD:8D: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX G GAIN /COLOR CORRECTION G SATURATION	OSD:8E: [Data]		QSD:8E	OSD:8E: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX G PHASE /COLOR CORRECTION G PHASE	OSD:8F: [Data]		QSD:8F	OSD:8F: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX G_Cy GAIN /COLOR CORRECTION G_Cy SATURATION	OSD:90: [Data]		QSD:90	OSD:90: [Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks					
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70
COLOR MATRIX G_Cy PHASE /COLOR CORRECTION G_Cy PHASE	OSD:91:[Data]		QSD:91	OSD:91:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX Cy GAIN /COLOR CORRECTION Cy SATURATION	OSD:92:[Data]		QSD:92	OSD:92:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX Cy PHASE /COLOR CORRECTION Cy PHASE	OSD:93:[Data]		QSD:93	OSD:93:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX Cy_B GAIN /COLOR CORRECTION Cy_G SATURATION	OSD:94:[Data]		QSD:94	OSD:94:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX Cy_B PHASE /COLOR CORRECTION Cy_B PHASE	OSD:95:[Data]		QSD:95	OSD:95:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX B GAIN /COLOR CORRECTION B SATURATION	OSD:96:[Data]		QSD:96	OSD:96:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX B PHASE /COLOR CORRECTION B PHASE	OSD:97:[Data]		QSD97	OSD:97:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX B_Mg GAIN /COLOR CORRECTION B_Mg SATURATION	OSD:80:[Data]		QSD:80	OSD:80:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX B_Mg PHASE /COLOR CORRECTION B_Mg PHASE	OSD:81:[Data]		QSD:81	OSD:81:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX Mg GAIN /COLOR CORRECTION Mg SATURATION	OSD:82:[Data]		QSD:82	OSD:82:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX Mg PHASE /COLOR CORRECTION Mg PHASE	OSD:83:[Data]		QSD:83	OSD:83:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX Mg_R GAIN /COLOR CORRECTION Mg_R SATURATION	OSD:84:[Data]		QSD:84	OSD:84:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks					
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/HE65/HE70	UE70
COLOR MATRIX Mg_R PHASE /COLOR CORRECTION Mg_R PHASE	OSD:85:[Data]		QSD:85	OSD:85:[Data]	01h - 80h - FFh	-127 - 0 - +127				V1.00	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
T PEDESTAL	OTP:[Data]		QTP	OTP:[Data]	000h - 096h - 12Ch	-150 - 0 - +150		V1.00 Data/15	V3.00 Data/15	V1.00	V1.00	V1.00 Data/15	V1.00 Data/15
R GAIN	ORI:[Data]		QRI	ORI:[Data]	000h - 096h - 12Ch	-150 - 0 - +150		V2.00 Data/5	V3.00 Data/5	V1.00	V1.00	V1.00 Data/5	V1.00 Data/5
B GAIN	OBI:[Data]		QBI	OBI:[Data]	000h - 096h - 12Ch	-150 - 0 - +150		V2.00 Data/5	V3.00 Data/5	V1.00	V1.00	V1.00 Data/5	V1.00 Data/5
R PEDESTAL	ORP:[Data]		QRP	ORP:[Data]	000h - 096h - 12Ch	-150 - 0 - +150				V1.00	V1.00 supports only -100~+100		
B PEDESTAL	OBP:[Data]		QBP	OBP:[Data]	000h - 096h - 12Ch	-150 - 0 - +150				V1.00	V1.00 supports only -100~+100		
3D-DNR	ODD:[Data]		QDD	ODD:[Data]	00 01 02	OFF LOW HIGH							
AUTO FOCUS	OAF:[Data]		QAF	OAF:[Data]	0 1	Manual FOCUS AUTO FOCUS		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
DIGITAL GAIN UP	ODG:[Data]		QDG	ODG:[Data]	0 1 2 3 4 5	0dB 6dB 12dB 18dB 24dB 30dB							
DIGITAL EXTENDER	ODE:[Data]		QDE	ODE:[Data]	0 1	OFF ON					V1.00	V1.00	V1.00
FILTER	OFT:[Data]		QFT	OFT:[Data]	0 1 2 3 4 0 1 2 3 4	IR Through Normal 1/16 ND 1/64 ND AW-HE130, HE40, HE70 AW-HE120, AK-HC1500, HC1800 Clear 1/4 ND 1/16 ND 1/64 ND 1/8 ND				V1.00 supports only Clear 1/4 ND 1/16 ND 1/64 ND	V1.00 supports only Clear 1/64 ND 1/8 ND		V1.00 0h: Clear 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND 8h: Auto ND
RED TALLY	TLR:[Data]				0 1	OFF ON							
GREEN TALLY	TLG:[Data]				0 1	OFF ON							

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
BLACK SHADING CORRECT (DIG)	OSA:C0:[Data]		QSA:C0	OSA:C0:[Data]	0 1		OFF ON							
M GAMMA@DRS OFF	OSA:01:[Data]		QSA:01	OSA:01:[Data]	6Ah - 79h - 97h		0.30 - 0.45 - 0.75							
M GAMMA@DRS ON	OSA:02:[Data]		QSA:02	OSA:02:[Data]	76h - 80h - 8Ah		-10 0 - +10							
R GAMMA@DRS OFF	OSA:03:[Data]		QSA:03	OSA:03:[Data]	71h - 80h - 8Fh		-15 0 - +15							
R GAMMA@DRS ON	OSA:04:[Data]		QSA:04	OSA:04:[Data]	76h - 80h - 8Ah		-10 0 - +10							
B GAMMA@DRS OFF	OSA:05:[Data]		QSA:05	OSA:05:[Data]	71h - 80h - 8Fh		-15 0 - +15							
B GAMMA@DRS ON	OSA:06:[Data]		QSA:06	OSA:06:[Data]	76h - 80h - 8Ah		-10 0 - +10							
M BLACK GAMMA	OSA:07:[Data]		QSA:07	OSA:07:[Data]	60h - 80h - A0h		-32 0 - +32							
R BLACK GAMMA	OSA:08:[Data]		QSA:08	OSA:08:[Data]	71h - 80h - 8Fh		-15 0 - +15							
B BLACK GAMMA	OSA:09:[Data]		QSA:09	OSA:09:[Data]	71h - 80h - 8Fh		-15 0 - +15							
GAMMA SW	OSA:0A:[Data]		QSA:0A	OSA:0A:[Data]	0 1		OFF ON							
BLACK GAMMA SW	OSA:0B:[Data]		QSA:0B	OSA:0B:[Data]	0 1		OFF ON							
EFFECT DEPTH	OSA:0C:[Data]		QSA:0C	OSA:0C:[Data]	1 - 5		1 - 5							
DRS SW	OSA:0D:[Data]		QSA:0D	OSA:0D:[Data]	0 1		OFF ON							

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
CINE GAMMA SELECT	OSA:0E:[Data]		QSA:0E	OSA:0E:[Data]	0 1		FILM REC VIDEO REC							
BLACK STRETCH LEVEL (@FILM MENU & FILM REC)	OSA:0F:[Data]		QSA:0F	OSA:0F:[Data]	00h - 1Eh		0 30							
DYNAMIC LEVEL (@FILM MENU & FILM REC)	OSA:10:[Data]		QSA:10	OSA:10:[Data]	0 1 2 3		200% 300% 400% 500%							
M KNEE POINT (@VIDEO MENU)	OSA:20:[Data]		QSA:20	OSA:20:[Data]	22h - 80h - B6h		70.00% - 93.50% - 107.00% (1step=0.25%)					V1.00		
M KNEE POINT (@FILM MENU & VIDEO REC)	OSA:21:[Data]		QSA:21	OSA:21:[Data]	62h - 80h - 9Eh		30% - 60% - 90%							
R KNEE POINT	OSA:22:[Data]		QSA:22	OSA:22:[Data]	1Ch - 80h - E4h		-25.00% - 0.00% - +25.00% (1step=0.25%)							
B KNEE POINT	OSA:23:[Data]		QSA:23	OSA:23:[Data]	1Ch - 80h - E4h		-25.00% - 0.00% - +25.00% (1step=0.25%)							
M KNEE SLOPE (@VIDEO MENU)	OSA:24:[Data]		QSA:24	OSA:24:[Data]	00h - 63h		0 99					V1.00		
M KNEE SLOPE (@FILM MENU & VIDEO REC)	OSA:25:[Data]		QSA:25	OSA:25:[Data]	7Ch - 80h - 85h		150% - 350% - 600% (1step=50%)							
R KNEE SLOPE (@VIDEO MENU)	OSA:26:[Data]		QSA:26	OSA:26:[Data]	1Dh - 80h - E3h		-99 - 0 - +99							
B KNEE SLOPE (@VIDEO MENU)	OSA:27:[Data]		QSA:27	OSA:27:[Data]	1Dh - 80h - E3h		-99 - 0 - +99							
A KNEE POINT (@VIDEO MENU)	OSA:28:[Data]		QSA:28	OSA:28:[Data]	4Ah - 80h - B6h		80.00% - 93.50% - 107.00% (1step=0.25%)							

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
A. KNEE LEVEL (@VIDEO MENU)	OSA:29:[Data]		QSA:29	OSA:29:[Data]	7Ch - 85h		100% - 109% (1step=0.25%)							
M WHITE CLIP LEVEL	OSA:2A:[Data]		QSA:2A	OSA:2A:[Data]	00h - 13h		90% - 109%					V1.00		
R WHITE CLIP LEVEL	OSA:2B:[Data]		QSA:2B	OSA:2B:[Data]	71h - 80h - 8Fh		-15% - 0% - +15%							
B WHITE CLIP LEVEL	OSA:2C:[Data]		QSA:2C	OSA:2C:[Data]	71h - 80h - 8Fh		-15% - 0% - +15%							
KNEE SW	OSA:2D:[Data]		QSA:2D	OSA:2D:[Data]	0 1 2		OFF MANUAL AUTO					V1.00		
WHITE CLIP	OSA:2E:[Data]		QSA:2E	OSA:2E:[Data]	0 1		OFF ON					V1.00		
HIGH COLOR	OSA:2F:[Data]		QSA:2F	OSA:2F:[Data]	0 1		OFF ON							
TOTAL DTL LEVEL	OSA:30:[Data]		QSA:30	OSA:30:[Data]	61h - 80h - 9Fh 61h - 80h - 9Fh		-31 - 0 - +31 <u>AW-HE130</u> 0 - +31 +62					V1.00	V1.00 supports only 81h(1)-91h(17) for TOTAL DTL LEVEL (LOW)	V1.00 supports only 81h(1)-91h(17) for TOTAL DTL LEVEL (LOW)
H DTL LEVEL	OSA:31:[Data]		QSA:31	OSA:31:[Data]	00h - 3Fh		0 - 63							
PEAK FREQUENCY	OSA:34:[Data]		QSA:34	OSA:34:[Data]	00h - 1Fh		0 - 31							
KNEE APERTURE	OSA:35:[Data]		QSA:35	OSA:35:[Data]	0 1		OFF ON							
KNEE APE LEVEL	OSA:36:[Data]		QSA:36	OSA:36:[Data]	0 - 5		0 - 5							
DETAIL(+)	OSA:38:[Data]		QSA:38	OSA:38:[Data]	61h - 80h - 9Fh		-31 0 - +31							
DETAIL(-)	OSA:39:[Data]		QSA:39	OSA:39:[Data]	61h - 80h - 9Fh		-31 0 - +31							
DETAIL CLIP	OSA:3A:[Data]		QSA:3A	OSA:3A:[Data]	00h - 3Fh		0 - 63							

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
DETAIL SOURCE	OSA:3B:[Data]		QSA:3B	OSA:3B:[Data]	0 1 2 3 4 5		(G+R)/2 (G+B)/2 (2G+B+R)/4 (3G+B)/4 R G							
SKIN TONE DETAIL (HD)	OSA:40:[Data]		QSA:40	OSA:40:[Data]	0 1		OFF ON							
SKIN GET	OSA:41:[Data]		QSA:41	OSA:41:[Data]	0 1 2		OFF ON GET	OFF:Wipe out the rectangle. ON:Display the rectangle. GET:Get Flesh Noise Suppress (SKIN) Color standard.						
SKIN DTL CORING (HD)	OSA:42:[Data]		QSA:42	OSA:42:[Data]	0 -		0 -							
SKIN TONE DTL Y MAX (HD)	OSA:43:[Data]		QSA:43	OSA:43:[Data]	00h -		0 -							
SKIN TONE DTL Y MIN (HD)	OSA:44:[Data]		QSA:44	OSA:44:[Data]	00h -		0 -							
SKIN TONE DTL I CENTER (HD)	OSA:45:[Data]		QSA:45	OSA:45:[Data]	00h -		0 -							
SKIN TONE DTL I WIDTH (HD)	OSA:46:[Data]		QSA:46	OSA:46:[Data]	00h -		0 -							
SKIN TONE DTL Q WIDTH (HD)	OSA:47:[Data]		QSA:47	OSA:47:[Data]	00h -		0 -							
SKIN TONE DTL Q PHASE (HD)	OSA:48:[Data]		QSA:48	OSA:48:[Data]	00h 80h -		-127 0 -							
SKIN TONE ZEBRA	OSA:49:[Data]		QSA:49	OSA:49:[Data]	0 1		OFF ON							
LOW GAIN	OSA:50:[Data]		QSA:50	OSA:50:[Data]	7Ah -		-6dB -							
					7Ch -		0dB -							
					80h -		12dB -							
					86h -		30dB -							
MID GAIN	OSA:51:[Data]		QSA:51	OSA:51:[Data]	7Ah -		-6dB -							
					7Ch -		0dB -							
					80h -		12dB -							
					86h -		30dB -							

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to contol	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
HIGH GAIN	OSA:52:[Data]		QSA:52	OSA:52:[Data]	7Ah - 7Ch - 80h - 86h	-6dB - 0dB - 12dB - 30dB								
A. IRIS WINDOW	OSA:53:[Data]		QSA:53	OSA:53:[Data]	0 1 2	NORM1 NORM2 CENTER								
IRIS MODE	OSA:54:[Data]		QSA:54	OSA:54:[Data]	0 1	LENS CAM								
IRIS GAIN @IRIS MODE = CAM	OSA:55:[Data]		QSA:55	OSA:55:[Data]	01h - 0Ah	1 (A. IRIS SLOW) - 10 (A. IRIS FAST)								
MODE @S. GAIN	OSA:60:[Data]		QSA:60	OSA:60:[Data]	0 1 2	S. GAIN1 S. GAIN2 S. GAIN3								
TOTAL GAIN@S. GAIN	---		QSA:61	OSA:61:[Data]	00h - 48h	0dB - 72dB								
GAIN@S. GAIN	OSA:62:[Data]		QSA:62	OSA:62:[Data]	00h 03h 06h - 1Eh 21h 24h	0dB 3dB 6dB - 30dB 33dB 36dB								
PIX MIX@S. GAIN	OSA:63:[Data]		QSA:63	OSA:63:[Data]	0 1	OFF +6dB								
V MIX@S. GAIN	OSA:64:[Data]		QSA:64	OSA:64:[Data]	0 1	OFF +6dB								
FRAME MIX@S. GAIN	OSA:65:[Data]		QSA:65	OSA:65:[Data]	00h 06h 0Ch 12h 18h 1Eh 80h	OFF +6dB +12dB +18dB +24dB +30dB AUTO	if use AUTO . Max Gain of AUTO is set up by the FRAME MIX MAX command (OSE:74:[Data])	V1.00 Support Only 00h(OFF)-12h(+18dB), 80h(AUTO)	V3.00 Support Only 00h(OFF)-12h(+18dB), 80h(AUTO)	V1.00 Support Only 00h(OFF)-18h(+24dB)	V1.00 Support Only 00h(OFF)-18h(+24dB)	V1.00 Support Only 00h(OFF)-18h(+24dB), 80h(AUTO)	V1.00 Support Only 00h(OFF)-18h(+24dB), 80h(AUTO)	
H DETAIL LEVEL @S. GAIN	OSA:66:[Data]		QSA:66	OSA:66:[Data]	00h - 3Fh	0 - 63								
CRISP @S. GAIN	OSA:67:[Data]		QSA:67	OSA:67:[Data]	00h - 1Fh	0 - 31								
LEVEL DEPENDENT @S. GAIN	OSA:68:[Data]		QSA:68	OSA:68:[Data]	00h - 0Fh	0 - 15								
PEAK FREQUENCY @S. GAIN	OSA:69:[Data]		QSA:69	OSA:69:[Data]	00h - 1Fh	0 - 31								
M GAMMA @S. GAIN & DRS OFF	OSA:6A:[Data]		QSA:6A	OSA:6A:[Data]	67h - 80h - 94h	0.30 - 0.55 - 0.75					V1.00			
M GAMMA @S. GAIN & DRS ON	OSA:6B:[Data]		QSA:6B	OSA:6B:[Data]	76h - 80h - 8Ah	-10 - 0 - +10								
M PED OFFSET @S. GAIN	OSA:6C:[Data]		QSA:6C	OSA:6C:[Data]	738h - 800h - 8C8h	-200 - 0 - +200								

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
R PED OFFSET @S. GAIN	OSA:6D:[Data]		QSA:6D	OSA:6D:[Data]	738h - 800h - 8C8h		-200 - 0 - +200							
B PED OFFSET @S. GAIN	OSA:6E:[Data]		QSA:6E	OSA:6E:[Data]	738h - 800h - 8C8h		-200 - 0 - +200							
SCAN REVERSE	OSA:70:[Data]		QSA:70	OSA:70:[Data]	0 1 2 3		OFF REVERSE1 (L/R REVERSE) REVERSE2 (U/D REVERSE) REVERSE3 (L/R & U/D REVERSE)							
FRAME RATE RANGE @VARIABLE FRAME	OSA:71:[Data]		QSA:71	OSA:71:[Data]	0 1		60-4 60-6							
FRAME RATE @VARIABLE FRAME	OSA:72:[Data]		QSA:72	OSA:72:[Data]	04h - 3Ch		4fps - 60fps							
MATRIX TABLE	OSA:00:[Data]		QSA:00	OSA:00:[Data]	0 1		TABLE A TABLE B							
D5600 @VIDEO MENU	OSA:80:[Data]		QSA:80	OSA:80:[Data]	0 1		OFF ON							
LIGHTING @FILM MENU	OSA:81:[Data]		QSA:81	OSA:81:[Data]	0 1		DAYLIGHT TUNGSTEN							
GAIN SELECT	OGS:[Data]		QGS	OGS:[Data]	01h 04h 08h 06h 0Ch 0Eh		LOW MID HIGH S. GAIN1 S. GAIN2 S. GAIN3							
CAM ID	OSA:82:[Data]		QSA:82	OSA:82:[Data]	0 1 2		OFF BAR ON							
CAM ID POSI	OSA:83:[Data]		QSA:83	OSA:83:[Data]	0 1 2 3		0(Upper left) 1(Upper right) 2(Lower left) 3(Lower right)							
MATRIX TABLE	OSA:84:[Data]		QSA:84	OSA:84:[Data]	0 1 2		OFF A B							
COLOR CORRECTION	OSA:85:[Data]		QSA:85	OSA:85:[Data]	0 1		OFF ON							
BAR SELECT	OSA:86:[Data]		QSA:86	OSA:86:[Data]	0 1 2 3 4 5 6		FULL (16:9) FULL (4:3) SMPTE (16:9) SMPTE (4:3) ARIB EIAJ SPRIT							

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks					
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/HE65/HE70	UE70
FORMAT	OSA:87:[Data]	QSA:87	OSA:87:[Data]		0h 1h 2h 3h 4h 5h 6h 7h 8h 9h Ah Bh Ch Dh Eh 10h 11h 12h 13h 14h 15h 16h 17h 18h 80h	720/60p 720/59.94p 720/50p 1080/60i 1080/59.94i 1080/50i 1080/30psF 1080/29.97psF 1080/25psF 1080/24psF 1080/23.98psF 480/59.94i 480/29.97psF 576/50i 576/25psF 1080/59.94p 1080/50p 480/59.94p 576/50p 1080/29.97p 1080/25p 1080/23.98p 2160/29.97p 2160/25p Auto		V1.00L01 [N Model] supports only 1h(720/59.94p), 4h(1080/59.94i), Bh(480/59.94i) [E, MC Model] supports only 2h(720/50p), 5h(1080/50i), Dh(576/50i) V2.00 [H Model/59.94Hz] supports only 1h(720/59.94p), 4h(1080/59.94i), Bh(480/59.94i), 10h(1080/59.94p), 7h(1080/29.97psF) [H Model/50Hz] supports only 2h(720/50p), 5h(1080/50i), Dh(576/50i), 11h(1808/50p), 8h(1080/25psf), 13h(576/50p) [S Model/59.94Hz] supports only 1h(720/59.94p), 4h(1080/59.94i), Bh(480/59.94i), 7h(1080/29.97psF) [S Model/50Hz] supports only 2h(720/50p), 5h(1080/50i), Dh(576/50i), 8h(1080/25psf)	V3.00 [H Model/59.94Hz] supports only 1h(720/59.94p), 4h(1080/59.94i), Bh(480/59.94i), 10h(1080/59.94p), 12h(480/59.94p) [H Model/50Hz] supports only 2h(720/50p), 5h(1080/50i), Dh(576/50i), 11h(1808/50p), 8h(1080/25psf), 13h(576/50p) [S Model/59.94Hz] supports only 1h(720/59.94p), 4h(1080/59.94i), Bh(480/59.94i) [S Model/50Hz] supports only 2h(720/50p), 5h(1080/50i), Dh(576/50i)	V1.00L01 [59.94Hz] supports only 1h(720/59.94p), 4h(1080/59.94i) 4h(1080/59.94i) 7h(1080/29.97psF) Ah(1080/23.98psF) 10h(1080/59.95p) 12h(480/59.94p) 14h(1080/29.97p) 16h(1080/23.98p) [50Hz] supports only 2h(720/50p) 5h(1080/50i) 8h(1080/25psF) 11h(1080/50p) 13h(576/50p) 15h(1080/25p)	V1.00 [59.94Hz] supports only 1h(720/59.94p) 4h(1080/59.94i) 7h(1080/29.97psF) Ah(1080/23.98psF) 10h(1080/59.95p) 12h(480/59.94p) 14h(1080/29.97p) 80h(Auto) [50Hz] supports only 2h(720/50p) 5h(1080/50i) 8h(1080/25psF) 11h(1080/50p) 15h(1080/25p) 80h(Auto) [50Hz] supports only 2h(720/50p) 5h(1080/50i) 8h(1080/25psF) 15h(1080/25p)	=== HDMI Model === [59.94Hz] supports only 1h(720/59.94p) 4h(1080/59.94i) 7h(1080/29.97psF) 14h(1080/29.97p) 80h(Auto) [50Hz] supports only 2h(720/50p) 5h(1080/50i) 8h(1080/25psF) 11h(1080/50p) 15h(1080/25p) 80h(Auto) [50Hz] supports only 2h(720/50p) 5h(1080/50i) 8h(1080/25psF) 15h(1080/25p)	v1.00 [59.94Hz] supports only 1h(720/59.94p) 4h(1080/59.94i) 7h(1080/29.97psF) 10h(1080/59.94p) 14h(1080/29.97p) 17h(2160/29.97p) 80h(Auto) [50Hz] supports only 2h(720/50p) 5h(1080/50i) 8h(1080/25psF) 11h(1080/50p) 15h(1080/25p) 18h(2160/25p) 80h(Auto)
STATUS	OSA:88:[Data]	QSA:88	OSA:88:[Data]		0 1	OFF ON		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
MENU ON BAR	OSA:89:[Data]	QSA:89	OSA:89:[Data]		0 1	OFF ON		---	---	---	---	---	---
MENU SEL	---	QSA:8A	OSA:8A:[Data]		0 1	VIDEO MENU FILM MENU		---	---	---	---	---	---
SHUTTER MODE	OSA:90:[Data]	QSA:90	OSA:90:[Data]		1 2 3	OFF ON SYNCHRO SCAN		---	---	---	---	---	---
SHUTTER SPEED	OSA:91:[Data]	QSA:91	OSA:91:[Data]		0 1 2 3 4 5 0 1 2 3 4 5	VIDEO MENU 1/100s 1/120s 1/250s 1/500s 1/1000s 1/2000s FILM MENU 180.0deg 172.8deg 144.0deg 120.0deg 90.0deg 45.0deg		---	---	---	---	---	---
GEN-LOCK INPUT	OSA:A0:[Data]	QSA:A0	OSA:A0:[Data]		0 1	OFF ON		---	---	---	---	---	---

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
H PHASE-COARSE @HD SYNC & 720	OSA:A1: [Data]		QSA:A1	OSA:A1: [Data]	58h - 80h - A8h	-40 - 0 - +40								
H PHASE-COARSE @HD SYNC & 1080	OSA:A2: [Data]		QSA:A2	OSA:A2: [Data]	44h - 80h - BCh	-60 - 0 - +60								
H PHASE-COARSE @SD SYNC	OSA:A3: [Data]		QSA:A3	OSA:A3: [Data]	08h - 80h - F8h	-120 - 0 - +120								
H PHASE-FINE @HD SYNC & 720	OSA:A4: [Data]		QSA:A4	OSA:A4: [Data]	53h - 80h - ADh	-45 - 0 - +45								
H PHASE-FINE @HD SYNC & 1080	OSA:A5: [Data]		QSA:A5	OSA:A5: [Data]	53h - 80h - ADh	-45 - 0 - +45								
H PHASE-FINE @SD SYNC	OSA:A6: [Data]		QSA:A6	OSA:A6: [Data]	53h - 80h - ADh	-45 - 0 - +45								
HD-SD PHASE CRS @HD SYNC	OSA:A7: [Data]		QSA:A7	OSA:A7: [Data]	79h - 80h - 88h	-7 - 0 - +7								
HD-SD PHASE FINE @HD SYNC	OSA:A8: [Data]		QSA:A8	OSA:A8: [Data]	1Dh - 80h - E3h	-99 - 0 - +99								
SD-HD PHASE CRS @SD SYNC	OSA:A9: [Data]		QSA:A9	OSA:A9: [Data]	7Ch - 80h - 84h	-4 - 0 - +4								
SD-HD PHASE FINE @SD SYNC (D/C BOARD)	OSA:AA: [Data]		QSA:AA	OSA:AA: [Data]	1Dh - 80h - E3h	-99 - 0 - +99								
HD/SD V PHASE @SD SYNC (D/C BOARD)	OSA:AB: [Data]		QSA:AB	OSA:AB: [Data]	0 1	HD SD								
SC COARSE @SD SYNC (D/C BOARD)	OSA:AC: [Data]		QSA:AC	OSA:AC: [Data]	1 - 8	1 - 8								
SC FINE @SD SYNC (D/C BOARD)	OSA:AD: [Data]		QSA:AD	OSA:AD: [Data]	19Ch - 200h - 264h	-100 - 0 - +100								
SC-H COARSE @HD SYNC or NO SYNC (D/C BOARD)	OSA:AE: [Data]		QSA:AE	OSA:AE: [Data]	1 - 8	1 - 8								
SC-H FINE @HD SYNC or NO SYNC	OSA:AF: [Data]		QSA:AF	OSA:AF: [Data]	19Ch - 200h - 264h	-100 - 0 - +100								

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
TOTAL DTL LEVEL HIGH	OSA:B1:[Data]		QSA:B1	OSA:B1:[Data]	61h - 80h - 9Fh		-31 - 0 - +31			Camera Main V3.05 supports only 82h(2)-92h(18) for TOTAL DTL LEVEL (HIGH)			V1.00 supports only 82h(2)-92h(18) for TOTAL DTL LEVEL (HIGH)	V1.00 supports only 82h(2)-92h(18) for TOTAL DTL LEVEL (HIGH)
TOTAL DTL LEVEL (D/C BOARD)	OSE:00:[Data]		QSE:00	OSE:00:[Data]	00h - 3Fh		0 - 63							
H DTL LEVEL (D/C BOARD)	OSE:01:[Data]		QSE:01	OSE:01:[Data]	00h - 3Fh		0 - 63							
CRISP (D/C BOARD)	OSE:02:[Data]		QSE:02	OSE:02:[Data]	00h - 3Fh		0 - 63							
PEAK FREQUENCY (D/C BOARD)	OSE:03:[Data]		QSE:03	OSE:03:[Data]	1 2 3 4 5 6 7		1.89MHz 2.18MHz 2.56MHz 3.17MHz 4.00MHz 5.28MHz 6.75MHz							
LEVEL DEPENDENT (D/C BOARD)	OSE:04:[Data]		QSE:04	OSE:04:[Data]	00h - 1Eh		0% - 30%							
DARK DETAIL (D/C BOARD)	OSE:05:[Data]		QSE:05	OSE:05:[Data]	0 - 7		0 (OFF) - 7							
KNEE APERTURE (D/C BOARD)	OSE:06:[Data]		QSE:06	OSE:06:[Data]	00h - 3Fh		0 - 63							
+CLIP (D/C BOARD)	OSE:07:[Data]		QSE:07	OSE:07:[Data]	00h - 3Fh		0 - 63							
-CLIP (D/C BOARD)	OSE:08:[Data]		QSE:08	OSE:08:[Data]	00h - 3Fh		0 - 63							
CORNER DETAIL (D/C BOARD)	OSE:09:[Data]		QSE:09	OSE:09:[Data]	00h - 1Fh		0 - 31							
CHROMA DETAIL (D/C BOARD)	OSE:0A:[Data]		QSE:0A	OSE:0A:[Data]	00h - 3Fh		0 - 63							
CHROMA DTL CRISP (D/C BOARD)	OSE:0B:[Data]		QSE:0B	OSE:0B:[Data]	00h - 3Fh		0 - 63							
DETAIL SOURCE (D/C BOARD)	OSE:0C:[Data]		QSE:0C	OSE:0C:[Data]	0 1 2 3 4		(G+R)/2 (G+B)/2 (2G+B+R)/4 (3G+B)/4 R							
SKIN TONE DETAIL (D/C BOARD)	OSE:10:[Data]		QSE:10	OSE:10:[Data]	0 1		OFF ON							
SKIN TONE LEVEL (D/C BOARD)	OSE:11:[Data]		QSE:11	OSE:11:[Data]	0 1 2		LOW MID HIGH							
SKIN TONE ZEBRA (D/C BOARD)	OSE:12:[Data]		QSE:12	OSE:12:[Data]	0 1		OFF ON							
SKIN TONE PHASE (D/C BOARD)	OSE:13:[Data]		QSE:13	OSE:13:[Data]	5Dh - 7Bh - 99h		93 - 123 - 153							
SKIN TONE WIDTH (D/C BOARD)	OSE:14:[Data]		QSE:14	OSE:14:[Data]	01h - 14h		1 - 20							
SKIN TONE CRISP (D/C BOARD)	OSE:15:[Data]		QSE:15	OSE:15:[Data]	0 - 7		0 - 7							
D/C MODE (D/C BOARD)	OSE:20:[Data]		QSE:20	OSE:20:[Data]	0 1 2 3		SIDE CUT SQUEEZE LetterBOX Link		V1.00	V3.00	V1.00	V1.00		

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks							
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70		
VBS SETUP (D/C BOARD)	OSE:21:[Data]		QSE:21	OSE:21:[Data]	0 1		0.0% 7.5%								
CHARACTER MIX (D/C BOARD)	OSE:22:[Data]		QSE:22	OSE:22:[Data]	0 1 2 3		ALL SD (VBS + SD-SDI) VBS SD-SDI								
2D LPF (D/C BOARD)	OSE:23:[Data]		QSE:23	OSE:23:[Data]	0 1 2 3		OFF LOW MID HIGH								
CHARACTER MIX (HD SDI BOARD)	OSE:30:[Data]		QSE:30	OSE:30:[Data]	0 1		ALL OPTION								
CHARACTER MIX SELECT	OSD:98:[Data1]:[Data2]		QSD:98:[Data1]	OSD:98:[Data1]:[Data2]	<u>Data1</u> 0 1 2 <u>Data2</u> 0 1 2		<u>Output</u> Browser/Video SDI/HDMI, Component OPTION <u>Character Mix Select</u> Off On Off By Browser							V3.00 supports only <u>Output</u> 0 (Browser/Video), 1 (SDI/HDMI, Component) <u>Character Mix Select</u> 2 (Off By Browser) is Valid When Output is 1 (SDI/HDMI, Component)	
ERROR NOTICE	---		QER	OER:[Data]	0 1		Normal Fan Error							V1.00 If the Camera made trouble, Camera sent "OER:[Data]" periodically.	
PRESET MATRIX SELECT	OSE:31:[Data]		QSE:31	OSE:31:[Data]	0 1 2 3		NORMAL EBU MATRIX NTSC MATRIX USER			V1.00 supports only 0 (NORMAL), 1 (EBU MATRIX), 2 (NTSC MATRIX) V2.00	V3.00	V1.00	V1.00	V1.00	V1.00
SOFT SKIN	OSE:32:[Data]		QSE:32	OSE:32:[Data]	0 1 2 3		OFF LOW MID HIGH			V1.00 supports only 0 (OFF), 1 (LOW), 3 (HIGH)	V3.00 supports only 0 (OFF), 1 (LOW), 3 (HIGH)			V1.00 supports only 0 (OFF), 1 (LOW), 3 (HIGH)	V1.00 supports only 0 (OFF), 1 (LOW), 3 (HIGH)
DRS SELECT	OSE:33:[Data]		QSE:33	OSE:33:[Data]	0 1 2 3		OFF LOW MID HIGH			V1.00 supports only 0 (OFF), 1 (LOW), 3 (HIGH)	V3.00 supports only 0 (OFF), 1 (LOW), 3 (HIGH)	V1.00	V1.00	V1.00 supports only 0 (OFF), 1 (LOW), 3 (HIGH)	V1.00 supports only 0 (OFF), 1 (LOW), 3 (HIGH)
HDMI COLOR	OSE:68:[Data]		QSE:68	OSE:68:[Data]	0 1 2 3		RGB (NOR) RGB (ENH) YpPr (422) YpPr (444)			V1.00	V3.00	V1.00			
PUSH AUTO FOCUS	OSE:69:[Data]		---	---	1		PUSH AUTO			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
DIGITAL ZOOM ENABLE	OSE:70:[Data]		QSE:70	OSE:70:[Data]	0 1		DISABLE ENABLE			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
PRESET SCOPE	OSE:71:[Data]		QSE:71	OSE:71:[Data]	0 1 2		MODE A MODE B MODE C			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
GAMMA TYPE	OSE:72:[Data]		QSE:72	OSE:72:[Data]	0 1 2 0 1 2 3 4	OFF NORMAL CINEMA AW-HE130 HD SD FILMLIKE1 FILMLIKE2 FILMLIKE3		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
BACK LIGHT COMPENSATION	OSE:73:[Data]		QSE:73	OSE:73:[Data]	0 1	OFF ON		V1.00	V3.00	---	---	V1.00	V1.00	
AUTO F. MIX MAX GAIN	OSE:74:[Data]		QSE:74	OSE:74:[Data]	00 01 02 03 04 05 06	(OFF) 6dB 12dB 18dB 24dB 30dB 36dB (HBK50:33dB)		V1.00 supports only 00(OFF)-03(18dB)	V3.00 supports only 00(OFF)-03(18dB)	---	---	V1.00 supports only 00(OFF)-03(18dB)	V1.00 supports only 00(OFF)-03(18dB)	
OSD Off With TALLY	OSE:75:[Data]		QSE:75	OSE:75:[Data]	0 1	OFF ON		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	
DIGITAL ZOOM MAGNIFICATION	OSE:76:[Data]		QSE:76	OSE:76:[Data]	0100 - 9999	*1.00 - *99.99		V1.00 supports only 0100(*1.00) - 1000(*10.00)	V3.00 supports only 0100(*1.00) - 1000(*10.00)	V1.00 supports only 0100(*1.00) - 1000(*10.00)	V1.00 supports only 0100(*1.00) - 1000(*10.00)	V1.00 supports only 0100(*1.00) - 1600(*16.00)	V1.00 supports only 0100(*1.00) - 1200(*12.00)	
BASE FREQUENCY SELECT	OSE:77:[Data]		QSE:77	OSE:77:[Data]	0 1	59.94Hz 50.00Hz		V2.00	V1.00	V1.00	V1.00	V1.00	V1.00	
MAXIMUM DIGITAL ZOOM	OSE:7A:[Data]		QSE:7A	OSE:7A:[Data]	02 - 18	x2 - x18		---	---	V1.00 supports only 02(x2) - 10(x10)	V1.00 supports only 02(x2) - 10(x10)	V1.00 supports only 02(x2) - 16(x16)	V1.00 supports only 02(x2) - 12(x12)	
RIGHT SW	DRT:[Data]		---	---	1h Ah	1Step 10Step		---	---	V1.00	V1.00	---	---	
LEFT SW	DLT:[Data]		---	---	1h Ah	1Step 10Step		---	---	V1.00	V1.00	---	---	
DAY-NIGHT	OSE:80:[Data]		QSE:80	OSE:80:[Data]	0 1	Day Night		---	---	---	---	---	---	
OIS(Optical Image Stabilizer)	OIS:[Data]		QIS	OIS:[Data]	0 1 2	Off On		---	---	---	V1.00	V1.00	V1.00	
Flash Band Comp	OFB:[Data]		QFB	OFB:[Data]	0 1	Off On		---	---	---	---	---	---	

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
FLESH NOISE SUPPRESS	OSD:A3:[Data]		QSD:A3	OSD:A3:[Data]	80h - 9Fh		0 - 31					V1.0		
MATRIX(R-G)	OSD:A4:[Data]		QSD:A4	OSD:A4:[Data]	41h - 80h - BFh		-63 - 0 - 63					V1.0		
MATRIX(R-B)	OSD:A5:[Data]		QSD:A5	OSD:A5:[Data]	41h - 80h - BFh		-63 - 0 - 63					V1.0		
MATRIX(G-R)	OSD:A6:[Data]		QSD:A6	OSD:A6:[Data]	41h - 80h - BFh		-63 - 0 - 63					V1.0		
MATRIX(G-B)	OSD:A7:[Data]		QSD:A7	OSD:A7:[Data]	41h - 80h - BFh		-63 - 0 - 63					V1.0		
MATRIX(B-R)	OSD:A8:[Data]		QSD:A8	OSD:A8:[Data]	41h - 80h - BFh		-63 - 0 - 63					V1.0		
MATRIX(B-G)	OSD:A9:[Data]		QSD:A9	OSD:A9:[Data]	41h - 80h - BFh		-63 - 0 - 63					V1.0		
COLOR MATRIX Mg,R,R GAIN /COLOR CORRECTION Mg,R,R SATURATION	OSD:9A:[Data]		QSD:9A	OSD:9A:[Data]	01h - 80h - FFh		-127 - 0 - +127					V1.0 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX Mg,R,R PHASE /COLOR CORRECTION Mg,R,R PHASE	OSD:9B:[Data]		QSD:9B	OSD:9B:[Data]	01h - 80h - FFh		-127 - 0 - +127					V1.0 supports only 41h(-63) - BFh(+63)		
COLOR MATRIX R,R,YI GAIN /COLOR CORRECTION R,R,YI SATURATION	OSD:9C:[Data]		QSD:9C	OSD:9C:[Data]	01h - 80h - FFh		-127 - 0 - +127					V1.0 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX R,R,YI PHASE /COLOR CORRECTION R,R,YI PHASE	OSD:9D:[Data]		QSD:9D	OSD:9D:[Data]	01h - 80h - FFh		-127 - 0 - +127					V1.0 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX R,YI,YI GAIN /COLOR CORRECTION R,YI,YI SATURATION	OSD:9E:[Data]		QSD:9E	OSD:9E:[Data]	01h - 80h - FFh		-127 - 0 - +127					V1.0 supports only 41h(-63) - BFh(+63)	V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX R,YI,YI PHASE /COLOR CORRECTION R,YI,YI PHASE	OSD:9F:[Data]		QSD:9F	OSD:9F:[Data]	01h - 80h - FFh		-127 - 0 - +127					V1.0 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
AUDIO	OSA:D0:[Data]		QSA:D0	OSA:D0:[Data]	0 1		OFF ON					V1.0	V1.00	V1.00
AUDIO INPUT VOLUME	OSA:D1:[Data]		QSA:D1	OSA:D1:[Data]	0 1 2 3 4 5		Mic High Mic Middle Mic Low Line High Line Middle Line Low					V1.0	V1.00	V1.00
AUDIO PLUGIN POWER	OSA:D2:[Data]		QSA:D2	OSA:D2:[Data]	0 1		OFF ON					V1.0	V1.00	V1.00

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks						
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70	
TALLY BRIGHTNESS	OSA:D3:[Data]		QSA:D3	OSA:D3:[Data]	0 1 2		LOW MID HIGH					V1.0		
NIGHT MODE SEL	OSD:B2:[Data]		QSD:B2	OSD:B2:[Data]	0 1		Manual Auto						V1.00	V1.00
i. ZOOM	OSD:B3:[Data]		QSD:B3	OSD:B3:[Data]	0 1		DISABLE ENABLE						V1.00	V1.00
HDR	OSD:B4:[Data]		QSD:B4	OSD:B4:[Data]	0 1 2 3		Off Low Mid High						V1.00 supports only 0(OFF), 1 (LOW), 3 (HIGH)	V1.00 supports only 0(OFF), 1 (LOW), 3 (HIGH)
COLOR MATRIX Cy_Cy_B GAIN /COLOR CORRECTION Cy_Cy_B	OSD:AA:[Data]		QSD:AA	OSD:AA:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX Cy_Cy_B PHASE /COLOR CORRECTION Cy_Cy_B PHASE	OSD:AB:[Data]		QSD:AB	OSD:AB:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX Cy_B_B GAIN /COLOR CORRECTION Cy_B_B SATURATION	OSD:AC:[Data]		QSD:AC	OSD:AC:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX Cy_B_B PHASE /COLOR CORRECTION Cy_B_B PHASE	OSD:AD:[Data]		QSD:AD	OSD:AD:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX B_B_Mg GAIN /COLOR CORRECTION B_B_Mg SATURATION	OSD:C0:[Data]		QSD:C0	OSD:C0:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX B_B_Mg PHASE /COLOR CORRECTION B_B_Mg PHASE	OSD:C1:[Data]		QSD:C1	OSD:C1:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX B_Mg_Mg GAIN /COLOR CORRECTION B_Mg_Mg	OSD:C2:[Data]		QSD:C2	OSD:C2:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX B_Mg_Mg PHASE /COLOR CORRECTION B_Mg_Mg PHASE	OSD:C3:[Data]		QSD:C3	OSD:C3:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX Yl_Yl_G GAIN /COLOR CORRECTION Yl_Yl_G SATURATION	OSD:C4:[Data]		QSD:C4	OSD:C4:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX Yl_Yl_G PHASE /COLOR CORRECTION Yl_Yl_G PHASE	OSD:C5:[Data]		QSD:C5	OSD:C5:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)
COLOR MATRIX Yl_G_G GAIN /COLOR CORRECTION Yl_G_G SATURATION	OSD:C6:[Data]		QSD:C6	OSD:C6:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 61h(-31) - 9Fh(+31)	V1.00 supports only 61h(-31) - 9Fh(+31)
COLOR MATRIX Yl_G_G PHASE /COLOR CORRECTION Yl_G_G PHASE	OSD:C7:[Data]		QSD:C7	OSD:C7:[Data]	01h - 80h - FFh		-127 - 0 - +127						V1.00 supports only 41h(-63) - BFh(+63)	V1.00 supports only 41h(-63) - BFh(+63)

ITEM	Control Command	Reply for Control Command	Confirmation Command	Reply for Confirmation Command	Data	Data Contents		Remarks							
						Control and Response to control	Response to Confirmation	HE50	HE60	HE120	HE130	HE40/ HE65/ HE70	UE70		
NIGHT-DAY LEVEL	OSD:B7:[Data]		QSD:B7	OSD:B7:[Data]	0 1 2		Low Mid High							V1.00	V1.00
Digital Extender Magnification	OSD:B8:[Data]		QSD:B8	OSD:B8:[Data]	0 1 2 3 4		x1.4 x2.0 x4.0 x6.0 x8.0								V1.00
Format_SDI	OSD:B9:[Data]		QSD:B9	OSD:B9:[Data]	0h 1h 2h 3h 4h 5h 6h 7h 8h 9h Ah Bh Ch Dh Eh 10h 11h 12h 13h 14h 15h 16h		720/60p 720/59.94p 720/50p 1080/60i 1080/59.94i 1080/50i 1080/30psF 1080/29.97psF 1080/25psF 1080/24psF 1080/23.98psF 480/59.94i 480/29.97psF 576/50i 576/25psF 1080/59.94p 1080/50p 480/59.94p 576/50p 1080/29.97p 1080/25p 1080/23.98p								V1.00 [59.94Hz] supports only 1h(720/59.94p) 4h(1080/59.94i) 7h(1080/29.97psF) 10h(1080/59.94p) 14h(1080/29.97p) [50Hz] supports only 2h(720/50p) 5h(1080/50i) 8h(1080/25psF) 11h(1080/50p) 15h(1080/25p)
Color Bars Type	OSD:BA:[Data]		QSD:BA	OSD:BA:[Data]	0 1		TYPE2(Full BAR/EBU) TYPE1(SMPTE)							V1.21+AW-SFU01	V1.00
ALC	OSD:BB:[Data]		QSD:BB	OSD:BB:[Data]	0 1		OFF ON							V1.21+AW-SFU01	V1.00
Equalize	OSD:BC:[Data]		QSD:BC	OSD:BC:[Data]	0 1 2		OFF LowCUT VOICE							V1.21+AW-SFU01	V1.00
Bars Title	OSD:BE:[Data]		QSD:BE	OSD:BE:[Data]	0 1		OFF ON							V1.21+AW-SFU01	V1.00
AutoShutterLimit	OSD:BF:[Data]		QSD:BE	OSD:BE:[Data]	0 1 2 3 4		[59.94Hz] Off [50Hz] Off 1/60 1/50 1/100 1/100 1/120 1/125 1/250 1/250								V1.00

P/T Control Protocol

This is a program to control Panasonic PAN/TILT system from PC by serial communication.

Method	Half Duplex
Communication Speed	9600bps
Data bit	8bit
Stop bit	1bit
Prity	None
Flow control	None

(Electrical Specification)

Connector : Modular 8pin

Compatible with RS422

4line system(TX+,TX-/send, RX+,RX-/Recieve)

(Process)

(1) PC — Command —> CAMERA

(2) CAMERA — Command —> PC (In most P/T commands, there is no reply.)

Normally it is processed as mentioned above, but in case of error, it ends by replying error code(*1) in (2).

(*1)Error code

Item	Error code	Contents
Unsupported	eR1[CR]	The Command is not supported by CAMERA.
System busy	eR2[CR]	CAMERA can not process the command for running the other processing.
Out of range	eR3[CR]	Data is out of range.

ex)1 PAN Stop command

```
# P 5 0 [CR]
H'23 H'50 H'35 H'30 H'0D
```


ITEM	Control Command	Confirmation Command	Response Command	Data	Data Contents		Remarks	HE50	HE60	HE120	HE130	HE40/HE65/HE70	UE70
					Control and Response to control	Response to Confirmation							
Power	#O[Data]	#O	p[Data]	0 f 1 n 2 3	Power OFF Power OFF Power ON Power ON ---	Power OFF Power OFF Power ON(w/ Camera TX) Power ON(wo/ Camera TX) Starting	Camera Power & P/T Control "Starting" is supported only Response Command.	with Camera TX -> Controller RX line	with Camera TX -> Controller RX line	with Camera TX -> Controller RX line	with Camera TX -> Controller RX line	with Camera TX -> Controller RX line	with Camera TX -> Controller RX line
Pan Speed Control	#P[Data]	---	pS[Data]	01 - 50 - 99	Left Max. Speed - Stop - Right Max. Speed			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Tilt Speed Control	#T[Data]	---	tS[Data]	01 - 50 - 99	Down Max. Speed - Stop - UP Max. Speed			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Zoom Speed Control	#Z[Data]	---	zS[Data]	01 - 49 50 51 - 99	Wide Max. Speed - Wide Min. Speed Stop Tele Min. Speed - Tele Max. Speed			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Zoom Position Control	#AXZ[Data]	#AXZ	axz[Data]	555h - FFFh	Wide - Tele			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Focus Speed Control	#F[Data]	---	fS[Data]	01 - 49 50 51 - 99	Near Max. Speed - Near Min. Speed Stop Far Min. Speed - Far Max. Speed			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Focus Position Control	#AXF[Data]	#AXF	axf[Data]	555h - FFFh	Near - Far			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Roll Speed Control	#RO[Data]	---	rO[Data]	01 - 49 50 51 - 99	CCW Max. Speed - CCW Min. Speed Stop CW Min. Speed - CW Max. Speed			---	---	---	---	---	---
Iris Control	#I[Data]	#I	iC[Data]	01 - 99	Iris Close - Iris Open			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Iris Control	#AXI[Data]	#AXI	axi[Data]	555h - FFFh	Iris Close - Iris Open			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Extender/AF Control	#D1[Data]	#D1	d1[Data]	0 1	OFF ON			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
ND Control	#D2[Data]	#D2	d2[Data]	0 1	OFF ON			---	---	---	---	---	---
Iris Auto/Manual	#D3[Data]	#D3	d3[Data]	0 1	Manual Iris Auto Iris			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Lamp Control	#D4[Data]	#D4	d4[Data]	0 1	OFF ON			---	---	---	---	---	---
Lamp Alarm	#D5	---	d5[Data]	0 1	Alarm OFF Alarm ON			---	---	---	---	---	---
OPTION SW Control	#D6[Data]	#D6	d6[Data]	0 1	OFF ON			V1.00	V3.00	---	V1.00	V1.00	V1.00
Defroster Control	#D7[Data]	---	d7[Data]	0 1	OFF ON			---	---	---	---	---	---
Wiper Control	#D8[Data]	---	d8[Data]	0 1	OFF ON			---	---	---	---	---	---
Heater/Fan Control	#D9[Data]	---	d9[Data]	0 1	OFF ON			---	---	---	---	---	---
Tally Control	#DA[Data]	#DA	dA[Data]	0 1	OFF ON			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Request Latest Recall Preset No.	---	#S	s[Data]	00 - 99 PH360,PH400,PH405,PH650	Preset 1 - Preset 100 PH360,PH400,PH405,PH650 Preset 01 - Preset 50			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Save Preset Memory	#M[Data]	---	s[Data]	00 - 99 PH360,PH400,PH405,PH650	Preset001 - Preset100 PH360,PH400,PH405,PH650 Preset 01 - Preset 50			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00
Recall Preset Memory	#R[Data]	---	s[Data]	00 - 99 PH360,PH400,PH405,PH650	Preset001 - Preset100 PH360,PH400,PH405,PH650 Preset 01 - Preset 50			V1.00	V3.00	V1.00	V1.00	V1.00	V1.00

ITEM	Control Command	Confirmation Command	Response Command	Data	Data Contents		Remarks	HE50	HE60	HE120	HE130	HE40/HE65/HE70	UE70
					Control and Response to control	Response to Confirmation							
Preset completion notification	---	---	q[Data]	00 - 99 PH360,PH400,PH405,PH650 00 - 49	Preset001 - Preset100 PH360,PH400,PH405,PH650 Preset_01 - Preset_50		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Preset Mode Setting	#RT[Data]	#RT	rt[Data]	0 1	Normal Diagonal		---	---	---	---	---	---	---
Limitation Setting	#L[Data]	---	l[Data]	Controller-> P/T 1 2 3 4 P/T-> Controller 0 1	Tilt Up Tilt Down Pan Left Pan Right	Release Set	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Landing Setting	#N[Data]	---	n[Data]	0 1	Just Landing Soft Landing		---	---	---	---	---	---	---
Request Zoom Position (Output D/A Data)	---	#GZ	gz[Data]	555h FFFh "----"	Wide Tele @Power OFF		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Request Focus Position (Output D/A Data)	---	#GF	gf[Data]	555h FFFh "----"	Near Far @Power OFF		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Request Iris Position (Output D/A Data)	---	#GI	gi[Data1][Data2]	[Data1] 555h FFFh "----" [Data2] 0 1	Close Open @Power OFF [Data2] Manual Iris Auto Iris	@Iris Manual	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Tilt Range	#AGL[Data]	#AGL	aGL[Data]	0 1	Narrow(190deg) Wide(300deg)		---	---	---	---	---	---	---
Request Software Verion	---	#V?	[Version Data]				---	---	---	---	---	---	---
TALLY Enable	#TAE[Data]	#TAE	tAE[Data]	0 1	Disable Enable		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Install Positon	#INS[Data]	#INS	iNS[Data]	0 1	Desktop Hanging		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Speed With Zoom POS	#SWZ[Data]	#SWZ	sWZ[Data]	0 1	OFF ON		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Pan/Tilt Absolute Position Control	#APC[Data1][Data2]	#APC	aPC[Data1][Data2]	[Data1] 0000h - 8000h - FFFFh [Data2] 0000h - 8000h - FFFFh	[Data1]Pan Position CCW Limit - Center - CW Limit [Data2]Tilt Position UP Limit - Center - DOWN Limit	[Data1]Pan Position CCW Limit - Center - CW Limit [Data2]Tilt Position UP Limit - Center - DOWN Limit	1 step is equivalent to 29.7 seconds V1.00 supports only Pan 2D08(CCW Limit)-D2F5(CW Limit) Tilt 5556(UP Limit)-8E38(DOWN Limit)	V3.00 supports only Pan 2D08(CCW Limit)-D2F5(CW Limit) Tilt 5556(UP Limit)-8E38(DOWN Limit)	V1.00 supports only Pan 2D08(CCW Limit)-D2F5(CW Limit) Tilt 1C73(UP Limit)-8E38(DOWN Limit)	V1.00 supports only Pan 2D08(CCW Limit)-D2F5(CW Limit) Tilt 5556(UP Limit)-8E38(DOWN Limit)	V1.00 supports only Pan 2D08(CCW Limit)-D2F5(CW Limit) Tilt 5556(UP Limit)-8E38(DOWN Limit)	V1.00 supports only Pan 2D08(CCW Limit)-D2F5(CW Limit) Tilt 5556(UP Limit)-8E38(DOWN Limit)	
Limitation Control	#LC[Data1][Data2]	#LC[Data1]	lC[Data1][Data2]	[Data1] 1 2 3 4 [Data2] 0 1	[Data1] Tilt Up Tilt Down Pan Left Pan Right [Data2] Release Set	[Data1] Tilt Up Tilt Down Pan Left Pan Right [Data2] Release Set	V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00

ITEM	Control Command	Confirmation Command	Response Command	Data	Data Contents		Remarks	HE50	HE60	HE120	HE130	HE40/HE65/HE70	UE70
					Control and Response to control	Response to Confirmation							
Pan Tilt Speed Control	#PTS[Data1][Data2]	---	pTS[Data1][Data2]	[Data1] 01 - 50 - 99 [Data2] 01 - 50 - 99	[Data1] Left Max. Speed - Stop - Right Max. Speed [Data2] Down Max. Speed - Stop - UP Max. Speed		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Wireless Control	#WLC[Data1]	#WLC	wLC[Data1]	0 1	Disable Enable		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
SOFTWARE VERSION	#CSV[Data1][Data2][Data3][Data4][Data5][Data6]	#QSV[Data1]	qSV[Data1][Data2][Data3][Data4][Data5][Data6]	[Data1] 0 1 2 3 4 5 6 7 8 9 [Data2] 00-99 [Data3] 00-99 [Data4] E L [Data5] 00-99 [data6] 0 1 2	[Data1] (Unit No.0) (Unit No.1) (Unit No.2) (Unit No.3) (Unit No.4) (Unit No.5) (Unit No.6) (Unit No.7) (Unit No.8) (Unit No.9) [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] Debug Build Release Build [Data5] REVISION [data6] NTSC PAL Other		[Data1] Pan Tilt CPU Camera CPU Camera FPGA Network CPU OUT FPGA reserve reserve reserve reserve Camera EEPROM reserve [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL Other	[Data1] Pan Tilt CPU Camera CPU Camera FPGA Network CPU OUT FPGA reserve reserve reserve Camera EEPROM reserve [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL Other	[Data1] Servo CPU CameraMain CPU Frontend FPGA Network CPU Backend FPGA Interface CPU Lens FPGA Interface EEPROM Camera EEPROM Lens EEPROM [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	[Data1] Servo CPU CameraMain CPU COM FPGA Network CPU AVIO FPGA Interface CPU Lens FPGA Interface EEPROM reserve [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	supports only #QSV[Data1] [Data1] Servo CPU Cam CPU FPGA BE CPU reserve Interface CPU reserve Interface EEPROM reserve [Data2] 00 [Data3] VERSION [Data4] L [Data5] 00 [data6] NTSC PAL	supports only #QSV[Data1] [Data1] Servo CPU Cam CPU FPGA BE CPU reserve Interface CPU reserve Interface EEPROM reserve [Data2] 00 [Data3] VERSION [Data4] L [Data5] 00 [data6] NTSC PAL	
Error Status Info.	---	#RER	rER[Data]	00h 01h 02h 03h 04h 05h 06h 07h 08h 09h 0Ah 0Bh - 17h - 19h - 21h 22h 23h 24h 25h - 30h 31h 32h 33h	Normal (Error1) (Error2) (Error3) (Error4) (Error5) (Error6) (Error7) (Error8) (Error9) (Error10) (Error11) - (Error23) - (Error25) - (Error27) (Error28) (Error29) (Error30) (Error31) (Error32) (Error33) (Error34) - (Error48) (Error49) (Error50) (Error51)		V1.00 Normal - Motor Driver Error Pan Sensor Error Tilt Sensor Error Controller RX Over run Error Controller RX Framing Error Network RX Over run Error Network RX Framing Error - - Controller RX Command Buffer Overflow - Network RX Command Buffer Overflow - System Error Spec Limit Over FPGA Config Error Network communication Error - Lvds Adjustmet_NG Bar_Signal_Check_NG - - -	V3.00 Normal - Motor Driver Error Pan Sensor Error Tilt Sensor Error Controller RX Over run Error Controller RX Framing Error Network RX Over run Error Network RX Framing Error - - Controller RX Command Buffer Overflow - Network RX Command Buffer Overflow - System Error Spec Limit Over FPGA Config Error Network communication Error - Lvds Adjustmet_NG Bar_Signal_Check_NG H_Sync_Check_NG HDMI_Check_NG	V1.00 Normal - Motor Driver Error Pan Sensor Error Tilt Sensor Error Controller RX Over run Error Controller RX Framing Error Network RX Over run Error Network RX Framing Error - - Controller RX Command Buffer Overflow - Network RX Command Buffer Overflow - System Error Spec Limit Over FPGA Config Error Network communication Error Lens Initialize Error - - - - - - - - -	V1.00 Normal - Motor Driver Error Pan Sensor Error Tilt Sensor Error Controller RX Over run Error Controller RX Framing Error Network RX Over run Error Network RX Framing Error - - Controller RX Command Buffer Overflow - Network RX Command Buffer Overflow - System Error Spec Limit Over FPGA Config Error CAMERA communication Error CAMERA RX Over run Error CAMERA RX Framing Error CAMERA RX Command Buffer Overflow	V1.00 supports only 00h Normal(No Error) 03h Motor Driver Error 04h Pan Sensor Error 05h Tilt Sensor Error 06h IF/FPGA UART Over run Error 07h IF/FPGA UART Framing Error 08h IF/NET UART Over run Error 09h IF/NET UART Framing Error 17h IF/FPGA UART Buffer Overflow 19h IF/NET UART Buffer Overflow 21h System Error(IF/SERVO Error) 22h PT Limit Over 24h NET Life-monitoring Error 25h BE Life-monitoring Error 26h IF/BE UART Buffer Overflow 27h IF/BE UART Framing Error 28h IF/BE UART Buffer Overflow 29h CAM Life-monitoring Error	V1.00 supports only 00h Normal(No Error) 03h Motor Driver Error 04h Pan Sensor Error 05h Tilt Sensor Error 06h IF/FPGA UART Over run Error 07h IF/FPGA UART Framing Error 08h IF/NET UART Over run Error 09h IF/NET UART Framing Error 17h IF/FPGA UART Buffer Overflow 19h IF/NET UART Buffer Overflow 21h System Error(IF/SERVO Error) 22h PT Limit Over 24h NET Life-monitoring Error 25h BE Life-monitoring Error 26h IF/BE UART Buffer Overflow 27h IF/BE UART Framing Error 28h IF/BE UART Buffer Overflow 29h CAM Life-monitoring Error	
Lens Position Information	---	#LPI	lPI[Data1][Data2][Data3]	[Data1] 555h - FFFh [Data2] 555h - FFFh [Data3] 555h - FFFh	[Data1]Zoom Position Wide - Tele [Data2]Focus Position Near - Far [Data3]Iris Position Close - Open		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	
Lens Position Information Control	#LPC[Data]	#LPC	lPC[Data]	0 1	Off On		V1.00	V3.00	V1.00	V1.00	V1.00	V1.00	V1.00
Smart Picture Flip	#SPF[Data]	#SPF	sPF[Data]	0 1	Off Auto		---	---	V1.00	V1.00	---	---	---
Flip Detect Angle	#FDA[Data]	#FDA	fDA[Data]	3Ch - 78h	60deg - 120deg		---	---	V1.00	V1.00	---	---	---
PinP Position	#PD[Data]	#PD	pD[Data]	0 1 2 3	Right Up Right Down Left Down Left Up		---	---	---	---	---	---	---
Camera/PinP Control	#CMP[Data]	#CMP	cMP[Data]	0 1	Camera Main PinP		---	---	---	---	---	---	---
Guide Line Control	#GDL[Data]	#GDL	gDL[Data]	0 1	Off On		---	---	---	---	---	---	---
IR Remote Controller ID	#RID[Data]	#RID	rID[Data]	0 1 2 3	01 02 03 04		---	---	---	---	V1.00	V1.00	V1.00

ITEM	Control Command	Confirmation Command	Response Command	Data	Data Contents		Remarks	HE50	HE60	HE120	HE130	HE40/HE65/HE70	UE70	
					Control and Response to control	Response to Confirmation								
Resolution Control	#RZL[Data]	#RZL	rZL[Data]	0 1	640x360 320x180							V1.00	V1.00	
P/T Relative Position Control	#RPC[Data1][Data2]	---	rPC[Data1][Data2]	[Data1] 0000h - 8000h - FFFFh [Data2] 0000h - 8000h - FFFFh	[Data1]Pan Position CCW Limit - Center - CW Limit [Data2]Tilt Position UP Limit - Center - DOWN Limit						V1.00	V1.00	V1.00	
Image Freeze During Preset	#PRF[Data]	#PRF	pRF[Data]	0 1	OFF ON							V1.00	V1.00	V1.00
Preset Speed Table	#PST[Data]	#PST	pST[Data]	0 1 2	SLOW MID FAST							V1.00	V1.00	V1.00
P/T Absolute Position Control w/Speed	#APS[Data1][Data2][Data3][Data4]	---	pPS[Data1][Data2][Data3][Data4]	[Data1] 0000h - 8000h - FFFFh [Data2] 0000h - 8000h - FFFFh [Data3] 00h - 1Dh [Data4] 0 1 2	[Data1]Pan Position CCW Limit - Center - CW Limit [Data2]Tilt Position UP Limit - Center - DOWN Limit [Data3]Preset Speed 1 - 30 [Data4]Preset Speed Table SLOW MID FAST						V1.00	V1.00	V1.00	
P/T Relative Position Control w/Speed	#RPS[Data1][Data2][Data3][Data4]	---	rPS[Data1][Data2][Data3][Data4]	[Data1] 0000h - 8000h - FFFFh [Data2] 0000h - 8000h - FFFFh [Data3] 00h - 1Dh [Data4] 0 1 2	[Data1]Pan Position CCW Limit - Center - CW Limit [Data2]Tilt Position UP Limit - Center - DOWN Limit [Data3]Preset Speed 1 - 30 [Data4]Preset Speed Table SLOW MID FAST						V1.00	V1.00	V1.00	